

Bluetooth Key Box

APP Operation Instruction



App Onboarding

Download “SUO” APP

1. Download “SUO” APP from the APP Store or Google Play by scanning the QR code.



APP Store




Google Play


2. Turn on the Bluetooth & GPS (for Android only) on your mobile device and launch the “SUO” APP.

※ “SUO” APP is compatible with iOS 10 (or later) & Android 4.3 (or later), connected by Bluetooth.


Pair New Lock




1. Click "+" icon to add new devices.



2. Please check the MAC Code Label on the Lock Box and select the same product ID.




3. Lock paired, press the device for 3 second to revise Device Name.



App Function

Login Permission Interface Function



1. ADMIN:

With complete functions, you can set up and manage 10 groups of USER and 10 groups of GUEST accounts, and inquire historical records. 6 digits password, the default password is 123456.

2. USER:

Users can lock and unlock the Lock box with no time limit. 4 digits password, the default password is 1234.

3. GUEST:

Guests can lock and unlock the Key Box within limited time. 4 digits password, no default password.

【Admin Mode】

Login as Admin (Default Password: 1 2 3 4 5 6)

The screenshot shows a mobile application login screen. At the top, there is a blue header with a back arrow and the word "Login". Below the header are three tabs: "ADMIN", "USER", and "GUEST", with "ADMIN" being the active tab. The main content area contains a "Password" input field with a circular callout "1" at its right end. Below the input field is a "Remember Password" toggle switch with a circular callout "2" at its right end. At the bottom of the form is a blue button labeled "LOGIN AS ADMIN" with a circular callout "3" at its right end.

1. Password:

Type your password.


2. Remember Password:

Click to turn on (lit up blue),
the input password will be recorded.

3. LOGIN AS ADMIN:

After you enter the password, click to login.

Interface Function



1. Return Button:

Return to Devices interfaces.

2. Lock Box Battery:

Shows the Key Box battery percentage.

3. Firmware Version:

Click to show the Firmware Version

4. Unlock / Lock Button:

Shows the lock(Red) or unlock(Green) status of the Key Box.

5. Lock Name:

Shows the lock name, can be changed on Device interfaces.



6. Home:

Operate the 1-5 functions.

7. Admin:


Change admin password, the touchpad password will be changed at the same time.

8. Users:

You can add or modify the IDs and passwords of 10 users.


9. Guests:

You can add or modify the IDs and passwords of 10 guests with limit access time.



10. Delete:

Delete all passwords of users and guests at once. Only the admin password will still exist.




11. History:


It can query 40 latest records that have been operated on, and the old records will be overwritten one by one.

Unlocking

1. Click the Red Button to turn it into Green Button.




2. The status indicator will light up green once unlocked.



Locking


Using APP

If you didn't open the Key Box, click the Green Button to turn it into Red Button to lock.




Auto Relock

Simple close the door in place, the Key Box will lock up automatically with a long beep.



【Admin Mode】


Manage 10 Users IDs and Passwords (Default ID: User 1 / Password: 1 2 3 4)



1. Click “+” in the end of User 1 to enter setting mode.
2. Enter user name, email(optional), password and confirm password, and click “SAVE”.
3. If you have entered the email, click “SHARE PASSWORD” to send the email to the email address.

【Admin Mode】

Manage 10 Guests IDs and Passwords (No Default Password)



1. Click “+” in the end of Guest 1 to enter setting mode.
2. Enter guest name, email(optional), password and confirm password.
3. Arrange access time, and click “SUBMIT” in the bottom of pages. (Please see the next page for more details)
4. Click “SAVE”.
5. If you have entered the email, click”SHARE PASSWORD” to send the email to the email address.

【Admin Mode】

Access Time

The image displays two screenshots of a mobile application interface for scheduling access times. Both screens have a blue header with a back arrow and the word "Schedule".

Left Screenshot (SIMPLE mode): The "SIMPLE" tab is selected and highlighted with a red box. Below the header, there are two tabs: "SIMPLE" and "DETAILED". The main content area is titled "Date" and shows a calendar view. The date "April 8 2021" is selected. Below the calendar, there are three radio button options: "All Hours" (selected), "AM7 ~ PM7", and "PM7 ~ AM7". At the bottom, there is a blue "SUBMIT" button.

Right Screenshot (DETAILED mode): The "DETAILED" tab is selected and highlighted with a red box. The main content area is titled "From" and shows a list of dates with time slots. The date "Today" is selected with a time slot of "09 00". Below this, there is a "To" section with a list of dates and time slots. The date "Fri Apr 9" is selected with a time slot of "14 00".

SIMPLE:

Choose a date, and a time period.

DETAILED:

Setting the time period personally.

【User Mode】

Login as User (Default ID: User 1 / Password: 1 2 3 4)

The screenshot shows a mobile application interface for logging in. At the top, there is a blue header with a back arrow and the word "Login". Below the header are three tabs: "ADMIN", "USER", and "GUEST". The "USER" tab is selected and has a circled "1" next to it. Below the tabs are three input fields: "ID" containing "User 1" with a circled "2", "Password" which is empty with a circled "3", and a "Remember Password" toggle switch which is turned off with a circled "4". At the bottom is a blue button labeled "LOGIN AS USER" with a circled "5".

1. Click "USER"
2. **ID:** Choose User 1 ~ User 10
3. **Password:** 4 digits password
4. **Remember Password:**
Click to turn on (lit up blue),
the input password will be recorded.
5. **LOGIN AS USER:**
After you enter the ID and password, click to login.

【Guest Mode】

Login as Guest (No Default Password)

The screenshot shows a mobile application interface for logging in as a guest. At the top, there is a blue header with a back arrow and the word "Login". Below the header are three tabs: "ADMIN", "USER", and "GUEST". The "GUEST" tab is selected and has a circled "1" next to it. Under the "GUEST" tab, there is an "ID" input field containing "Guest 1" with a circled "2" next to it. Below the ID field is a "Password" input field with a circled "3" next to it. Under the password field is a "Remember Password" toggle switch, which is currently turned off, with a circled "4" next to it. At the bottom of the form is a blue button labeled "LOGIN AS GUEST" with a circled "5" next to it.

1. Click "GUEST"
 2. **ID:** Choose Guest 1 ~ Guest 10
 3. **Password:** 4 digits password
 4. **Remember Password:**
Click to turn on (lit up blue),
the input password will be recorded.
 5. **LOGIN AS GUEST:**
After you enter the ID and password, click to login.
- ※ The password is invalid if it's not use within its activation period.

Touchpad Unlocking

【User】

Instruction:

Enter User ID + User password,
total 6 digits.


User ID:

User 1=01, User 2=02,....., User 10=10

Example:

ID: User 1=01 ; Password: 1234

Enter: 011234



【Guest】

Instruction:

Enter Guest ID + Guest password,
total 6 digits.


Guest ID :

Guest 1=11, Guest 2=12,....., Guest 10=20

Example:

ID: Guest 1=11 ; Password: 1234

Enter: 111234



Troubleshooting

Q1. App Download / Device Compatibility

- “SUO” app is available in the App Store and the Google Play Store.

iOS Version: 10 or later.

Android Version: 4.3 or later.

Q2. Why can't the App add a device?

- The Key Box's battery power is drained:


Please check if the Key Box is still working,

if not, please provide emergency power by Micro USB jump-start port on the Lock Box and replace the batteries.

- In mobile device's settings, make sure that Bluetooth is turned on.

Check if you have connected with “KBXXXXXXXXXXXX”(X=Lock BOX MAC code)on the Bluetooth interface.

Q3. The password is invalid when login as Admin on the App



- The Key Box's battery power is drained. Please refer to Q2.
- Typing incorrect password, please check if the password is correct.
- Your mobile device might running out of RAM: Close recently used apps to release the RAM, or restart your mobile device.
- Turn on the GPS on your mobile device (for Android only).
- The Key Box is paired with other mobile device. The Key Box can only be paired with one mobile device at once. To change the user, please turn off the Bluetooth of the paired mobile device, and turn on the Bluetooth of the new mobile device again.
- Location permission options (for Android only). Please choose "Allow all the time" or "Allow only while using the app" (As shown on the left).

Q4. The password is invalid when login as User or Guest on the App

- The Key Box's battery power is drained. Please refer to Q2.
- Typing incorrect ID or password, you can check your ID and password by touchpad unlock. Please refer to <Touchpad Unlocking> page.
- Admin didn't create the ID for user or guest, you can check your ID and password by touchpad unlock.
- The ID have been removed, you can check your ID and password by touchpad unlock.
- Your phone might running out of RAM, please refer to Q3.
- Turn on the GPS on your mobile device (for Android only).
- Location permission options (for Android only), please refer to Q3.
- The Key Box is paired with other mobile device, please refer to Q3.

Q5. Cannot SHARE PASSWORD

- Please check if you have entered correct email address.
- Make sure your mobile device have connected to the internet.